

channel	function	type of control	effect	decimal		percentage	
1	master dimmer	proportional	adjust luminous output intensity from 0 to 100%	0	- 255	0%	- 100%
2	white tone	step	select the primary WHITE color	0	- 9	0%	- 4%
			WHITE 7000 °K	10	- 21	4%	- 8%
			WHITE 6500 °K	22	- 33	9%	- 13%
			WHITE 6000 °K	34	- 45	13%	- 18%
			WHITE 5500 °K	46	- 57	18%	- 22%
			WHITE 5000 °K	58	- 69	23%	- 27%
			WHITE 4500 °K	70	- 81	27%	- 32%
			WHITE 4000 °K	82	- 93	32%	- 36%
			WHITE 3500 °K	94	- 105	37%	- 41%
			WHITE 3200 °K	106	- 117	42%	- 46%
		WHITE 3000 °K	118	- 128	46%	- 50%	
		proportional	adjust proportionally white color temperature from 3000°K to 7000°K	129	- 255	51%	- 100%
3	zoom	proportional	proportional control of zoom from narrow to wide beam	0	- 255	0%	- 100%
4	strobe	step	no effect	0	- 9	0%	- 4%
		proportional	variable speed strobing effect, from slow to fast	10	- 57	4%	- 22%
		step	stop strobe	58	- 59	23%	- 23%
		proportional	sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	60	- 108	24%	- 42%
		step	stop strobe	109	- 110	43%	- 43%
		proportional	sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast)	111	- 159	44%	- 62%
		step	stop strobe	160	- 161	63%	- 63%
		proportional	random strobe effect with variable speed from slow to fast and synchronised colour temperature selected	162	- 207	64%	- 81%
		step	stop strobe	208	- 209	82%	- 82%
		proportional	random strobe effect with variable speed from slow to fast and non-synchronised colour temperature	210	- 255	82%	- 100%
5	reset and special functions	step	park, no functions	0	- 9	0%	- 4%
			no functions	10	- 71	4%	- 28%
			reset	72	- 102	28%	- 40%
			no functions	103	- 133	40%	- 52%
			LCD display off	134	- 185	53%	- 73%
			LCD display on	186	- 199	73%	- 78%
			led control frequency tuning 1000 Hz	200	- 205	78%	- 80%
			led control frequency tuning 1500 Hz	206	- 211	81%	- 83%
			led control frequency tuning 2000 Hz	212	- 217	83%	- 85%
			led control frequency tuning 2500 Hz	218	- 223	85%	- 87%
			led control frequency tuning 3000 Hz	224	- 229	88%	- 90%
			led control frequency tuning 3500 Hz	230	- 235	90%	- 92%
			led control frequency tuning 4000 Hz	236	- 241	93%	- 95%
			led control frequency tuning 4500 Hz	242	- 247	95%	- 97%
led control frequency tuning 5000 Hz	248	- 255	97%	- 100%			

NOTE 1: channel 2 macros are available in conjunction with dimmer

Fixture: Reflection VariWhite	Table name: DMX 512 function
Table number: 295	Edition: 1
	Date: 31/01/2011