

# DMX chart LEDko T/D +

## DMX modes

DMX channels ↓	5 channels	1 channels
1	Master Dimmer	Master Dimmer
2	Spare Channel	
3	Dimmer Fine	
4	Strobe	
5	Special Function	

## DMX Chart 5, 1 channels

channel	function	type of control	effect	decimal	percentage
1	1	master dimmer	proportional	adjust luminous output intensity from 0 to 100%	0 - 255 0% - 100%
2	-	spare channel	step	no effect	0 - 255 0% - 100%
3	-	dimmer fine	proportional	fine dimmer control 16 bit	0 - 255 0% - 100%
4	-	strobe	step	no effect	0 - 9 0% - 4%
			proportional	variable speed strobing effect, from slow to fast	10 - 57 4% - 22%
			step	stop strobe	58 - 59 23% - 23%
			proportional	sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	60 - 108 24% - 42%
			step	stop strobe	109 - 110 43% - 43%
			proportional	sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast)	111 - 159 44% - 62%
			step	stop strobe	160 - 161 63% - 63%
			proportional	random strobe effect with variable speed from slow to fast	162 - 207 64% - 81%
			step	stop strobe	208 - 209 82% - 82%
			proportional	random strobe effect with variable speed from slow to fast	210 - 255 82% - 100%
5	-	special functions	step	park	0 - 9 0% - 4%
				600 Hz	10 - 22 4% - 9%
				no effect	23 - 84 9% - 33%
				fan at SILENT mode	85 - 96 33% - 38%
				fan at STUDIO mode	97 - 108 38% - 42%
				fan at AUTO mode	109 - 120 43% - 47%
			proportional	fan speed control	121 - 133 47% - 52%
			step	enables the automatic display blackout	134 - 185 53% - 73%
				disables the automatic display blackout	186 - 199 73% - 78%
				LED control frequency tuning 1.500 Hz	200 - 205 78% - 80%
				LED control frequency tuning 2.000 Hz	206 - 211 81% - 83%
				LED control frequency tuning 5.000 Hz	212 - 217 83% - 85%
				no effect	218 - 240 85% - 94%
LED control frequency tuning 20.000 Hz	241 - 255 95% - 100%				