

DMX chart - Risalto + Fixed White

DMX modes

| DMX channels ↓ | 5 channels | 1 channels |
|----------------|------------------|---------------|
| 1 | Master Dimmer | Master Dimmer |
| 2 | Spare Channel | |
| 3 | Dimmer Fine | |
| 4 | Strobe | |
| 5 | Special Function | |

5 and 1 channels

| channel | | function | type of control | effect | decimal | percentage |
|--|-----------|-------------------|-----------------|--|-----------|------------|
| 1 | 1 | master dimmer | proportional | adjust luminous output intensity from 0 to 100% | 0 - 255 | 0% - 100% |
| 2 | - | spare channel | step | no effect | 0 - 255 | 0% - 100% |
| 3 | - | dimmer fine | proportional | fine dimmer control 16 bit | 0 - 255 | 0% - 100% |
| 4 | - | strobe | step | no effect | 0 - 9 | 0% - 4% |
| | | | proportional | variable speed strobing effect, from slow to fast | 10 - 57 | 4% - 22% |
| | | | step | stop strobe | 58 - 59 | 23% - 23% |
| | | | proportional | sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast) | 60 - 108 | 24% - 42% |
| | | | step | stop strobe | 109 - 110 | 43% - 43% |
| | | | proportional | sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast) | 111 - 159 | 44% - 62% |
| | | | step | stop strobe | 160 - 161 | 63% - 63% |
| | | | proportional | random strobe effect with variable speed from slow to fast | 162 - 207 | 64% - 81% |
| | | | step | stop strobe | 208 - 209 | 82% - 82% |
| | | | proportional | random strobe effect with variable speed from slow to fast | 210 - 255 | 82% - 100% |
| 5 | - | special functions | step | park | 0 - 9 | 0% - 4% |
| | | | | 600 Hz | 10 - 22 | 4% - 9% |
| | | | | no effect | 23 - 84 | 9% - 33% |
| | | | | fan at SILENT mode | 85 - 96 | 33% - 38% |
| | | | | fan at STUDIO mode | 97 - 108 | 38% - 42% |
| | | | | fan at AUTO mode | 109 - 120 | 43% - 47% |
| | | | proportional | fan speed control | 121 - 133 | 47% - 52% |
| | | | step | enables the automatic display blackout | 134 - 185 | 53% - 73% |
| | | | | disables the automatic display blackout | 186 - 199 | 73% - 78% |
| | | | | LED control frequency tuning 1.500 Hz | 200 - 205 | 78% - 80% |
| | | | | LED control frequency tuning 2.000 Hz | 206 - 211 | 81% - 83% |
| | | | | LED control frequency tuning 5.000 Hz | 212 - 217 | 83% - 85% |
| | | | | no effect | 218 - 240 | 85% - 94% |
| LED control frequency tuning 20.000 Hz | 241 - 255 | 95% - 100% | | | | |