

MiniLEDko Profile - DMX chart

DMX modes

DMX channels ↓	5 channels	1 channel
1	Master Dimmer	Master Dimmer
2	Spare Channel	
3	Dimmer Fine	
4	Strobe	
5	Special Function	

DMX Chart 5/1 channels

channel		function	type of control	effect	decimal	percentage
1	1	master dimmer	proportional	adjust luminous output intensity from 0 to 100%	0 - 255	0% - 100%
2	-	spare channel	step	no effect	0 - 255	0% - 100%
3	-	dimmer fine	proportional	fine dimmer control 16 bit	0 - 255	0% - 100%
4	-	strobe	step	no effect	0 - 9	0% - 4%
			proportional	variable speed strobing effect, from slow to fast	10 - 57	4% - 22%
			step	stop strobe	58 - 59	23% - 23%
			proportional	sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	60 - 108	24% - 42%
			step	stop strobe	109 - 110	43% - 43%
			proportional	sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast)	111 - 159	44% - 62%
			step	stop strobe	160 - 161	63% - 63%
			proportional	random strobe effect with variable speed from slow to fast	162 - 207	64% - 81%
			step	stop strobe	208 - 209	82% - 82%
			proportional	random strobe effect with variable speed from slow to fast	210 - 255	82% - 100%
5	-	special functions	step	park	0 - 9	0% - 4%
				600 Hz	10 - 22	4% - 9%
				no effect	23 - 199	9% - 78%
				LED control frequency tuning 1.500 Hz	200 - 205	78% - 80%
				LED control frequency tuning 2.000 Hz	206 - 211	81% - 83%
				LED control frequency tuning 5.000 Hz	212 - 217	83% - 85%
				no effect	218 - 240	85% - 94%
				LED control frequency tuning 20.000 Hz	241 - 255	95% - 100%