

| channel | | function | type of control | effect | decimal | | percentage | |
|--------------------------------|---|-------------------|-----------------|---|---------|---|------------|--------|
| 5 | 1 | | | | | | | |
| 1 | 1 | master dimmer | proportional | adjust luminous output intensity from 0 to 100% | 0 | - 255 | 0% | - 100% |
| 2 | - | spare channel | step | no effect | 0 | - 255 | 0% | - 100% |
| 3 | - | dimmer fine | proportional | fine dimmer control 16 bit | 0 | - 255 | 0% | - 100% |
| 4 | - | strobe | step | no effect | 0 | - 9 | 0% | - 4% |
| | | | proportional | variable speed strobing effect, from slow to fast | 10 | - 57 | 4% | - 22% |
| | | | step | stop strobe | 58 | - 59 | 23% | - 23% |
| | | | proportional | sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast) | 60 | - 108 | 24% | - 42% |
| | | | step | stop strobe | 109 | - 110 | 43% | - 43% |
| | | | proportional | sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast) | 111 | - 159 | 44% | - 62% |
| | | | step | stop strobe | 160 | - 161 | 63% | - 63% |
| | | | proportional | random strobe effect with variable speed from slow to fast | 162 | - 207 | 64% | - 81% |
| | | | step | stop strobe | 208 | - 209 | 82% | - 82% |
| | | | proportional | random strobe effect with variable speed from slow to fast | 210 | - 255 | 82% | - 100% |
| 5 | - | special functions | step | park | 0 | - 9 | 0% | - 4% |
| | | | | 600 Hz | 10 | 84 | 4% | 33% |
| | | | | fan at Low-noise speed | 85 | - 96 | 33% | - 38% |
| | | | | fan at Studio speed | 97 | 108 | 38% | 42% |
| | | | | fan at Auto-silent speed | 109 | 120 | 43% | 47% |
| | | | proportional | fan speed control | 121 | - 133 | 47% | - 52% |
| | | | | enables the automatic display blackout | 134 | - 185 | 53% | - 73% |
| | | | | disables the automatic display blackout | 186 | - 199 | 73% | - 78% |
| | | | | LED control frequency tuning 1.000 Hz | 200 | - 205 | 78% | - 80% |
| | | | | LED control frequency tuning 3.000 Hz | 206 | 211 | 81% | 83% |
| | | | | LED control frequency tuning 5.000 Hz | 212 | 217 | 83% | 85% |
| | | | | no effect | 218 | 247 | 85% | 97% |
| | | | | LED control frequency tuning 20.000 Hz | 248 | 255 | 97% | 100% |
| Projector: Otello T / D | | | | Chart name: DMX512 function | | software version: 0.017or following | | |
| Edition: 2 | | | | Date: 04.02.2021 | | | | |