

StripLite Led RGB-W DMX Chart (eng)

zones	channel	function	type of control	effect	decimal	percentage
	1	master dimmer	proportional	adjust luminous output intensity from 0 to 100%	0 - 255	0% - 100%
zone 1	2	red	proportional	proportional control of the percentage of red colour from 0 to 100%	0 - 255	0% - 100%
	3	green	proportional	proportional control of the percentage of green colour from 0 to 100%	0 - 255	0% - 100%
	4	blue	proportional	proportional control of the percentage of blue colour from 0 to 100%	0 - 255	0% - 100%
	5	white	proportional	proportional control of the percentage of white light from 0 to 100%	0 - 255	0% - 100%
	zone 2	6	red	proportional	proportional control of the percentage of red colour from 0 to 100%	0 - 255
7		green	proportional	proportional control of the percentage of green colour from 0 to 100%	0 - 255	0% - 100%
8		blue	proportional	proportional control of the percentage of blue colour from 0 to 100%	0 - 255	0% - 100%
9		white	proportional	proportional control of the percentage of white light from 0 to 100%	0 - 255	0% - 100%
10	strobe effect	step	no effect	0 - 9	0% - 4%	
		proportional	variable speed strobing effect, from slow to fast	10 - 57	4% - 22%	
		step	stop strobe	58 - 59	23% - 23%	
		proportional	sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	60 - 108	24% - 42%	
		step	stop strobe	109 - 110	43% - 43%	
		proportional	sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast)	111 - 159	44% - 62%	
		step	stop strobe	160 - 161	63% - 63%	
		proportional	random strobe effect with variable speed from slow to fast and synchronised colours	162 - 207	64% - 81%	
		step	stop strobe	208 - 209	82% - 82%	
11	flicker free control T.V.	step	standard frequency 600 Hz	0 - 9	0% - 4%	
			led control frequency tuning 1000 Hz	10 - 36	4% - 14%	
			led control frequency tuning 1500 Hz	37 - 63	15% - 25%	
			led control frequency tuning 2000 Hz	64 - 90	25% - 35%	
			led control frequency tuning 2500 Hz	91 - 117	36% - 46%	
			led control frequency tuning 3000 Hz	118 - 144	46% - 56%	
			led control frequency tuning 3500 Hz	145 - 171	57% - 67%	
			led control frequency tuning 4000 Hz	172 - 198	67% - 78%	
			led control frequency tuning 4500 Hz	199 - 225	78% - 88%	
			led control frequency tuning 5000 Hz	226 - 255	89% - 100%	

note 1: channel 11 can be enabled by dip-switch number 6 (function T.V.)

Projector: StripLite Led RGB-W

Table name: DMX 512 functions

Table number: 279

Edition: 2/RGBW

Date: 10/02/2008