

Reflection LEDko Variwhite Series 2

DMX Chart (eng)

channel	function	type of control	effect	decimal	percentage
1	1	master dimmer	proportional	adjust luminous output intensity from 0 to 100%	0 - 255 0% - 100%
				3200K	0 - 9 0% - 4%
				2700K	10 - 16 4% - 6%
				2800K	17 - 23 7% - 9%
				2900K	24 - 30 9% - 12%
				3000K	31 - 37 12% - 15%
				3100K	38 - 44 15% - 17%
				3200K	45 - 51 18% - 20%
				3300K	52 - 57 20% - 22%
				3400K	58 - 63 23% - 25%
				3500K	64 - 69 25% - 27%
				3600K	70 - 75 27% - 29%
				3700K	76 - 81 30% - 32%
				3800K	82 - 87 32% - 34%
				3900K	88 - 93 35% - 36%
				4000K	94 - 99 37% - 39%
				4100K	100 - 105 39% - 41%
				4200K	106 - 111 42% - 44%
				4300K	112 - 117 44% - 46%
				4400K	118 - 123 46% - 48%
				4500K	124 - 129 49% - 51%
2	-	white temperature	step	4600K	130 - 135 51% - 53%
				4700K	136 - 141 53% - 55%
				4800K	142 - 147 56% - 58%
				4900K	148 - 153 58% - 60%
				5000K	154 - 159 60% - 62%
				5100K	160 - 165 63% - 65%
				5200K	166 - 171 65% - 67%
				5300K	172 - 177 67% - 69%
				5400K	178 - 183 70% - 72%
				5500K	184 - 189 72% - 74%
				5600K	190 - 195 75% - 76%
				5700K	196 - 201 77% - 79%
				5800K	202 - 207 79% - 81%
				5900K	208 - 213 82% - 84%
				6000K	214 - 219 84% - 86%
				6100K	220 - 225 86% - 88%
				6200K	226 - 231 89% - 91%
				6300K	232 - 237 91% - 93%
				6400K	238 - 243 93% - 95%
				6500K	244 - 249 96% - 98%
				5600K	250 - 255 98% - 100%
3	-	dimmer fine	proportional	fine dimmer control 16 bit	0 - 255 0% - 100%

Reflection LEDko Variwhite Series 2
DMX Chart (eng)

channel	function	type of control	effect	decimal	percentage
4 -	strobe	step	no effect	0 - 9	0% - 4%
		proportional	variable speed strobing effect, from slow to fast	10 - 57	4% - 22%
		step	stop strobe	58 - 59	23% - 23%
		proportional	sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	60 - 108	24% - 42%
		step	stop strobe	109 - 110	43% - 43%
		proportional	sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast)	111 - 159	44% - 62%
		step	stop strobe	160 - 161	63% - 63%
		proportional	random strobe effect with variable speed from slow to fast and synchronised colour temperature selected	162 - 207	64% - 81%
		step	stop strobe	208 - 209	82% - 82%
		proportional	random strobe effect with variable speed from slow to fast and non-synchronised colour temperature	210 - 255	82% - 100%
5 -	special function	step	no effect	0 - 71	0% - 28%
			600 Hz	72 - 84	28% - 33%
			fan at low-noise speed	85 - 96	33% - 38%
			fan at auto-silent speed	97 - 108	38% - 42%
			proportional fan speed control	109 - 120	43% - 47%
		step	no effect	121 - 133	47% - 52%
			LCD display off	134 - 185	53% - 73%
			LCD display on	186 - 199	73% - 78%
			LED control frequency tuning 1000Hz	200 - 205	78% - 80%
			LED control frequency tuning 3000Hz	206 - 211	81% - 83%
			LED control frequency tuning 6000Hz	212 - 217	83% - 85%
			LED control frequency tuning 8000Hz	218 - 223	85% - 87%
			LED control frequency tuning 10000Hz	224 - 229	88% - 90%
			LED control frequency tuning 12000Hz	230 - 235	90% - 92%
			LED control frequency tuning 14000Hz	236 - 241	93% - 95%
			LED control frequency tuning 16000Hz	242 - 247	95% - 97%
			LED control frequency tuning 19000Hz	248 - 255	97% - 100%

NOTE: The one channel function mode can be selected through the DMX function menu. The color of the light will be the last selected when changing mode.

Fixture: LEDko Variwhite Series 2
Table name: DMX 512 functions
Tabella numero: 356
Edizione: 1
Date: 18.04.2017