

DMX table Strobe C4 (eng)

channel [mod. 4ch]	channel [Mod. 3ch]	function	type of control	effect	decimal	percentage
1	1	dimmer	step	blackout	0 - 10	0% - 4%
			proportional	proportional control of power, from min to max	11 - 255	4% - 100%
2	2	flash length	step	no effect	0 - 10	0% - 4%
			proportional	proportional control of the flash length from min to max	11 - 255	4% - 100%
3	3	speed frequency flash rate	step	No flash, single strobe	0 - 10	0% - 4%
			proportional	proportional control of the flash frequency from min to max	11 - 255	4% - 100%
4		effects	step	no effect	0 - 10	0% - 4%
			proportional	ramp up (opening, slow pulse)	11 - 51	4% - 20%
			proportional	ramp down	52 - 92	20% - 36%
			proportional	ramp up-down	93 - 133	36% - 52%
			proportional	lightning storm	134 - 174	53% - 68%
			proportional	normal random	175 - 215	69% - 84%
			proportional	blinder random	216 - 255	85% - 100%
Nota: 3 channels mode is enabled lifting dip switch with the function "3ch".						
Projector: Strobe C4			Table name: DMX 512 functions			
Table number: 295		Edition: 0	Date: 05/05/2009			