

channel	function	type of control	effect	decimal	percentage
1	master dimmer	proportional	adjusts luminous output intensity from 0 to 100%	0 - 255	0% - 100%
2	red	proportional	proportional control of the percentage of red colour from 0 to 100%	0 - 255	0% - 100%
3	green	proportional	proportional control of the percentage of green colour from 0 to 100%	0 - 255	0% - 100%
4	blue	proportional	proportional control of the percentage of blue colour from 0 to 100%	0 - 255	0% - 100%
5	white	proportional	proportional control of the percentage of white light from 0 to 100%	0 - 255	0% - 100%
6	strobe effect	step	no effect	0 - 9	0% - 4%
		proportional	variable speed strobing effect, from slow to fast	10 - 57	4% - 22%
		step	stop strobe	58 - 59	23% - 23%
		proportional	sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	60 - 108	24% - 42%
		step	stop strobe	109 - 110	43% - 43%
		proportional	sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast)	111 - 159	44% - 62%
		step	stop strobe	160 - 161	63% - 63%
		proportional	random strobe effect with variable speed from slow to fast and synchronised colours	162 - 207	64% - 81%
step	stop strobe	208 - 209	82% - 82%		
proportional	random strobe effect with variable speed from slow to fast and non-synchronised colours	210 - 255	82% - 100%		
7	automated functions	step	no effect	0 - 9	0% - 4%
		proportional	automated colors program 1; fade speed between colours from fast to slow (from 1 second to 1 minute)	10 - 50	4% - 20%
			automated colors program 2; fade speed between colours from fast to slow (from 1 second to 1 minute)	51 - 91	20% - 36%
			automated colors program 3; fade speed between colours from fast to slow (from 1 second to 1 minute)	92 - 132	36% - 52%
			automated colors program 4; fade speed between colours from fast to slow (from 1 second to 1 minute)	133 - 173	52% - 68%
			random program repeat; fade speed between colours from fast to slow (from 1 second to 1 minute)	174 - 214	68% - 84%
repeat all programs in sequence; fade speed between colours from fast to slow (from 1 second to 1 minute)	215 - 255	84% - 100%			
8	special functions	step	no effect	0 - 9	0% - 4%
		proportional	control of the pause time between colours (steps) of the program selected from channel 7; the pause time is adjustable proportionally from 1 second to 3.30 minutes	10 - 135	4% - 53%
		step	park, no functions	136 - 179	53% - 70%
			led control frequency tuning 1000 Hz	180 - 188	71% - 74%
			led control frequency tuning 1500 Hz	189 - 197	74% - 77%
			led control frequency tuning 2000 Hz	198 - 206	78% - 81%
			led control frequency tuning 2500 Hz	207 - 215	81% - 84%
			led control frequency tuning 3000 Hz	216 - 224	85% - 88%
			led control frequency tuning 3500 Hz	225 - 233	88% - 91%
			led control frequency tuning 4000 Hz	234 - 242	92% - 95%
			led control frequency tuning 4500 Hz	243 - 251	95% - 98%
led control frequency tuning 5000 Hz	252 - 255	99% - 100%			
Projector: Stage Lite Led sc			Table name: DMX 512 functions		
Tabel number: 290		Edition: 0	Date: 05/10/2010		