

**Tabella DMX StageLite Led (eng)**  
 Zone (16ch)

zones	channel	function	type of control	effect	decimal	percentage
	1	master dimmer	proportional	adjust luminous output intensity from 0 to 100%	0 - 255	0% - 100%
Zone 1	2	red	proportional	proportional control of the percentage of red colour from 0 to 100%	0 - 255	0% - 100%
	3	green	proportional	proportional control of the percentage of green colour from 0 to 100%	0 - 255	0% - 100%
	4	blue	proportional	proportional control of the percentage of blue colour from 0 to 100%	0 - 255	0% - 100%
	5	white	proportional	proportional control of the percentage of white light from 0 to 100%	0 - 255	0% - 100%
Zone 2	6	red	proportional	proportional control of the percentage of red colour from 0 to 100%	0 - 255	0% - 100%
	7	green	proportional	proportional control of the percentage of green colour from 0 to 100%	0 - 255	0% - 100%
	8	blue	proportional	proportional control of the percentage of blue colour from 0 to 100%	0 - 255	0% - 100%
	9	white	proportional	proportional control of the percentage of white light from 0 to 100%	0 - 255	0% - 100%
10	strobe effect	step	no effect	0 - 9	0% - 4%	
		proportional	variable speed strobing effect, from slow to fast	10 - 57	4% - 22%	
		step	stop strobe	58 - 59	23% - 23%	
		proportional	sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	60 - 108	24% - 42%	
		step	stop strobe	109 - 110	43% - 43%	
		proportional	sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast)	111 - 159	44% - 62%	
		step	stop strobe	160 - 161	63% - 63%	
		proportional	random strobe effect with variable speed from slow to fast and synchronised colours	162 - 207	64% - 81%	
		step	stop strobe	208 - 209	82% - 82%	
proportional	random strobe effect with variable speed from slow to fast and non-synchronised colours	210 - 255	82% - 100%			
11	led line 1	proportional	proportional movement of lower led line in 180°	0 - 255	0% - 100%	
12	led line 2	proportional	proportional movement of central led line in 180°	0 - 255	0% - 100%	
13	led line 3	proportional	proportional movement of upper led line in 180°	0 - 255	0% - 100%	
14	automated functions and fade speed	proportional	no effect	0 - 9	0% - 4%	
			automated colors program 1; fade speed between colours from fast to slow (from 0,05 second to 1 minute)	10 - 40	4% - 16%	
			automated colors program 2; fade speed between colours from fast to slow (from 0,05 second to 1 minute)	41 - 71	16% - 28%	
			automated colors program 3; fade speed between colours from fast to slow (from 0,05 second to 1 minute)	72 - 102	28% - 40%	
			automated colors program 4; fade speed between colours from fast to slow (from 0,05 second to 1 minute, colors selected from ch. 2 to ch. 9)	103 - 133	40% - 52%	
			automated colors program 5; fade speed between colours from fast to slow (from 0,05 second to 1 minute, colors selected from ch. 2 to ch. 9)	134 - 164	53% - 64%	
			automated colors program 6; fade speed between colours from fast to slow (from 0,05 second to 1 minute, colors selected from ch. 2 to ch. 9)	165 - 195	65% - 76%	
			automated colors program 7; fade speed between colours from fast to slow (from 0,05 second to 1 minute, colors selected from ch. 2 to ch. 9)	196 - 225	77% - 88%	
			automated colors program 8; fade speed between colours from fast to slow (from 0,05 second to 1 minute, colors selected from ch. 2 to ch. 9)	226 - 255	89% - 100%	

**Tabella DMX StageLite Led (eng)**  
 Zone (16ch)

zones	channel	function	type of control	effect	decimal	percentage
15		effects movement	step	no effect	0 - 9	0% - 4%
				position 1	10 - 19	4% - 7%
				position 2	20 - 39	8% - 15%
				position 3	40 - 59	16% - 23%
				position 4	60 - 79	24% - 31%
				position 5	80 - 99	31% - 39%
			proportional	position 6	100 - 119	39% - 47%
				automated movement program 1 with proportional control over increasing speed	120 - 146	47% - 57%
				automated movement program 2 with proportional control over increasing speed	147 - 173	58% - 68%
				automated movement program 3 with proportional control over increasing speed	174 - 200	68% - 78%
				automated movement program 4 with proportional control over increasing speed	201 - 227	79% - 89%
automated movement program 5 with proportional control over increasing speed	228 - 255	89% - 100%				
16		motors reset and special functions	step	no effect	0 - 9	0% - 4%
			proportional	control of the pause time between colours (steps) of the program selected from channel 14; the pause time is adjustable proportionally from 1 second to 3.30 minutes	10 - 135	4% - 53%
			step	motors reset	136 - 170	53% - 67%
				park, no functions	171 - 179	67% - 70%
				led control frequency tuning 1000 Hz	180 - 188	71% - 74%
				led control frequency tuning 1500 Hz	189 - 197	74% - 77%
				led control frequency tuning 2000 Hz	198 - 206	78% - 81%
				led control frequency tuning 2500 Hz	207 - 215	81% - 84%
				led control frequency tuning 3000 Hz	216 - 224	85% - 88%
				led control frequency tuning 3500 Hz	225 - 233	88% - 91%
				led control frequency tuning 4000 Hz	234 - 242	92% - 95%
				led control frequency tuning 4500 Hz	243 - 251	95% - 98%
			led control frequency tuning 5000 Hz	252 - 255	99% - 100%	
<b>Projector: StageLite Led (Zone)</b>				<b>Table name: DMX 512 functions</b>		
<b>Table number: 290</b>		<b>Edition: 1</b>	<b>Date: 20/02/2009</b>			