

channel		function	type of control	effect	decimal		percentage		
1	1	master dimmer	proportional	adjust luminous output intensity from 0% to 100%	0	- 255	0%	- 100%	
2	-	spare channel	step	no effect	0	- 255	0%	- 100%	
3	-	dimmer fine	proportional	fine dimmer control 16 bit	0	- 255	0%	- 100%	
4	-	strobe effect	step	no effect	0	- 9	0%	- 100%	
			proportional	variable speed strobing effect, from slow to fast	10	- 57	4%	- 22%	
			step	stop strobe	58	- 59	23%	- 23%	
			proportional	sequenced pulsed strobing effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	60	- 108	24%	- 42%	
			step	stop strobe	109	- 110	43%	- 43%	
			proportional	sequenced pulsed strobe, fast closing, slow opening (variable speed pulsing, from slow to fast)	111	- 159	44%	- 62%	
			step	stop strobe	160	- 161	63%	- 63%	
			proportional	strobe effect with random flashes and synchronous colors (variable speed from slow to fast)	162	- 207	64%	- 81%	
			step	stop strobe	208	- 209	82%	- 82%	
			proportional	strobe effect with random flashes and synchronous colors (variable speed from slow to fast)	210	- 255	82%	- 100%	
5	-	special function	step	park	0	- 9	0%	- 4%	
				no effect	10	- 71	4%	- 28%	
				600 Hz	72	- 84	28%	- 33%	
				fan at low-noise speed	85	- 96	33%	- 38%	
				fan at auto speed	97	- 108	38%	- 42%	
			proportional	fan speed control from minimum to maximum	109	- 120	43%	- 47%	
			step	no effect	121	- 133	47%	- 52%	
				enables the automatic display blackout	134	- 185	53%	- 73%	
				disables the automatic display blackout	186	- 199	73%	- 78%	
				LED control frequency tuning 1.000 Hz	200	- 205	78%	- 80%	
				LED control frequency tuning 3.000 Hz	206	- 211	81%	- 83%	
				LED control frequency tuning 6.000 Hz	212	- 217	83%	- 85%	
				LED control frequency tuning 8.000 Hz	218	- 223	85%	- 87%	
				LED control frequency tuning 10.000 Hz	224	- 229	88%	- 90%	
				LED control frequency tuning 12.000 Hz	230	- 235	90%	- 92%	
				LED control frequency tuning 14.000 Hz	236	- 241	93%	- 95%	
				LED control frequency tuning 16.000 Hz	242	- 247	95%	- 97%	
				LED control frequency tuning 19.000 Hz	248	- 255	97%	- 100%	
				<b>Projector:</b> SoftLite Led Tungsten				<b>Chart name:</b> DMX512 function	
<b>Edition:</b> 2				<b>Date:</b> 10.10.2019					