

channel	function	type of control	effect	decimal	percentage
1	dimmer	step	closed	0 - 7	0% - 3%
		proportional	from close to open	8 - 255	3% - 100%
2	cyan	proportional	proportional cyan control from white to cyan	0 - 255	0% - 100%
3	magenta	proportional	proportional magenta control from white to magenta	0 - 255	0% - 100%
4	yellow	proportional	proportional yellow control from white to yellow	0 - 255	0% - 100%
5	right lamp on-off	step	park, no function	0 - 10	0% - 4%
			right lamp off	11 - 29	4% - 11%
			park, no function	30 - 140	12% - 55%
			right lamp on	141 - 255	55% - 100%
6	left lamp on-off and motors reset	step	park, no function	0 - 10	0% - 4%
			left lamp off	11 - 29	4% - 11%
			cmy reset (once only)	30 - 135	12% - 53%
			cmy and dimmer reset (once only)	136 - 170	53% - 67%
			park, no function	171 - 240	67% - 94%
			left lamp on	241 - 255	95% - 100%
<b>Note 1: back panel can inhibit lamp off function.</b>					
<b>Note 2: lamp on-off and motors reset functions has a delay time of 6 second to prevent accidental activation.</b>					
<b>Note 3: on/off lamp mode is not affected unless an opposite value is received.</b>					
Fixture type: coemar Panorama Power MK2		Chart name: DMX 512			
Chart number: 258		Release: 1		Date: 03/06/2005	