

StripLite Led RGB-W compact DMX Chart (eng)

| channel | function | type of control | effect | decimal | percentage |
|---------|----------------------|-----------------|--|-----------|------------|
| 1 | master dimmer | proportional | adjust luminous output intensity from 0 to 100% | 0 - 255 | 0% - 100% |
| 2 | red | proportional | proportional control of the percentage of red colour from 0 to 100% | 0 - 255 | 0% - 100% |
| 3 | green | proportional | proportional control of the percentage of green colour from 0 to 100% | 0 - 255 | 0% - 100% |
| 4 | blue | proportional | proportional control of the percentage of blue colour from 0 to 100% | 0 - 255 | 0% - 100% |
| 5 | white | proportional | proportional control of the percentage of white light from 0 to 100% | 0 - 255 | 0% - 100% |
| 6 | strobe effect | step | no effect | 0 - 9 | 0% - 4% |
| | | proportional | variable speed strobing effect, from slow to fast | 10 - 57 | 4% - 22% |
| | | step | stop strobe | 58 - 59 | 23% - 23% |
| | | proportional | sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast) | 60 - 108 | 24% - 42% |
| | | step | stop strobe | 109 - 110 | 43% - 43% |
| | | proportional | sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast) | 111 - 159 | 44% - 62% |
| | | step | stop strobe | 160 - 161 | 63% - 63% |
| | | proportional | random strobe effect with variable speed from slow to fast and synchronised colours | 162 - 207 | 64% - 81% |
| | | step | stop strobe | 208 - 209 | 82% - 82% |
| | | proportional | random strobe effect with variable speed from slow to fast and non-synchronised colours | 210 - 255 | 82% - 100% |

Note 1: this compact version is enabled by switch on the dip (compact 6 ch) of control panel.

Projector: StripLite Led RGB-W compact

Table name: DMX 512 functions

Table number: 279

Edition: 1/RGBW

Date: 16/02/2007