

StripLite Led RGB DMX Chart (eng)

zones	channel	function	type of control	effect	decimal	percentage
	1	master dimmer	proportional	adjust luminous output intensity from 0 to 100%	0 - 255	0% - 100%
zone 1	2	red	proportional	proportional control of the percentage of red colour from 0 to 100%	0 - 255	0% - 100%
	3	green	proportional	proportional control of the percentage of green colour from 0 to 100%	0 - 255	0% - 100%
	4	blue	proportional	proportional control of the percentage of blue colour from 0 to 100%	0 - 255	0% - 100%
	5	no function	step	spare channel, allows the compatibility with RGB-W version	0 - 255	0% - 100%
zone 2	6	red	proportional	proportional control of the percentage of red colour from 0 to 100%	0 - 255	0% - 100%
	7	green	proportional	proportional control of the percentage of green colour from 0 to 100%	0 - 255	0% - 100%
	8	blue	proportional	proportional control of the percentage of blue colour from 0 to 100%	0 - 255	0% - 100%
	9	no function	step	spare channel, allows the compatibility with RGB-W version	0 - 255	0% - 100%
10	strobe effect	step	no effect	0 - 9	0% - 4%	
		proportional	variable speed strobing effect, from slow to fast	10 - 57	4% - 22%	
		step	stop strobe	58 - 59	23% - 23%	
		proportional	sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	60 - 108	24% - 42%	
		step	stop strobe	109 - 110	43% - 43%	
		proportional	sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast)	111 - 159	44% - 62%	
		step	stop strobe	160 - 161	63% - 63%	
		proportional	random strobe effect with variable speed from slow to fast and synchronised colours	162 - 207	64% - 81%	
		step	stop strobe	208 - 209	82% - 82%	
proportional	random strobe effect with variable speed from slow to fast and non-synchronised colours	210 - 255	82% - 100%			
Projector: StripLite Led RGB			Table name: DMX 512 functions			
Table number: 279		Edition: 1/RGB	Date: 16/02/2007			