

**DMX table Strobe C4 (eng)**  
**Compact mode**

channel	function	type of control	effect	decimal	percentage
1	flash length	step	no effect	0 - 10	0% - 4%
		proportional	proportional control of the flash length from min to max	11 - 255	4% - 100%
2	speed frequency flash rate	step	No flash, single strobe	0 - 10	0% - 4%
		proportional	proportional control of the flash frequency from min to max	11 - 255	4% - 100%
<b>Nota: 2 channels mode is enabled lifting dip switch with the function "2ch".</b>					
<b>Projector: Strobe C4</b>			<b>Table name: DMX 512 functions compact</b>		
<b>Table number: 295</b>	<b>Edition: 0</b>	<b>Date: 05/05/2009</b>			