


Technical Brochure



DR1 + Plus



Controllers Series

DR1 + Plus

Display replicator

DR1 + Plus

SPECIFICATIONS

Connected to a PC allows to replicate and control all the Coemar fixtures' displays on the network via DMX 512 or Artnet

Modifies projector settings in groups or individually

Artnet / DMX converter

Allows to visualize a digital display also for products with dip-switches

Softwares upgrades

Transparent data flow from Artnet or DMX 512 controllers

Can be used as a controller with programs like Freestyler

Remote control until 250 different ID and projectors

PHYSICAL SIZE

Length: 150 mm (5.91 in)

Width: 80 mm (3.15 in)

Height: 50 mm (1.97 in)

Weight: 0.2 Kg (0.44 lbs)

CONTROL PROTOCOL AND PROGRAMMING

USITT DMX512/1990

Ethernet

Setting and addressing: virtual LCD display

Full version software included

ELECTRICAL SPECIFICATIONS / CONNECTIONS

Power supply: via USB port

DMX data In/Out: XLR 5 M/F

Ethernet RJ45 port

USB port





Coemar Lighting S.r.l.

Via Carpenedolo, 90

46043 Castiglione delle Stiviere

Mantova - Italy

ph. +39 0376 1514412

fax +39 0376 1514380

www.coemar.com

info@coemar.com