

Risalto Led  
Tabella DMX (5/1 ch)

channel		function	type of control	effect	decimal		percentage	
5 ch	1 ch							
1	1	master dimmer	proportional	adjust luminous output intensity from 0 to 100%	0	- 255	0%	- 100%
2	-	spare channel	step	no effect	0	- 255	0%	- 100%
3	-	dimmer fine	proportional	fine dimmer control 16 bit	0	- 255	0%	- 100%
4	-	strobe effect	step	no effect	0	- 9	0%	- 4%
			proportional	variable speed strobing effect, from slow to fast	10	- 57	4%	- 22%
			step	stop strobe	58	- 59	23%	- 23%
			proportional	sequenced pulsed strobe, slow closing, fast opening (variable speed pulsing, from slow to fast)	60	- 108	24%	- 42%
			step	stop strobe	109	- 110	43%	- 43%
			proportional	sequenced pulsed strobe, fast closing, slow opening (variable speed pulsing, from slow to fast)	111	- 159	44%	- 62%
			step	stop strobe	160	- 161	63%	- 63%
			proportional	strobe effect with random flashes and synchronous colours (variable speed from slow to fast)	162	- 207	64%	- 81%
			step	stop strobe	208	- 209	82%	- 82%
proportional	strobe effect with random flashes and synchronous colours (variable speed from slow to fast)	210	- 255	82%	- 100%			
5	-	special functions	step	no effect	0	- 71	0%	- 28%
				600 Hz	72	- 84	28%	- 33%
				fan at low-noise speed	85	- 96	33%	- 38%
				fan at auto speed	97	- 108	38%	- 42%
			proportional	fan speed control from minimum to maximum	109	- 120	43%	- 47%
			step	no effect	121	- 133	47%	- 52%
				LCD display off	134	- 185	53%	- 73%
				LCD display on	186	- 199	73%	- 78%
				LED control frequency tuning 1000 Hz	200	- 205	78%	- 80%
				LED control frequency tuning 3000Hz	206	- 211	81%	- 83%
				LED control frequency tuning 6000Hz	212	- 217	83%	- 85%
				LED control frequency tuning 8000Hz	218	- 223	85%	- 87%
				LED control frequency tuning 10000Hz	224	- 229	88%	- 90%
				LED control frequency tuning 12000Hz	230	- 235	90%	- 92%
				LED control frequency tuning 14000Hz	236	- 241	93%	- 95%
LED control frequency tuning 16000Hz	242	- 247		95%	- 97%			
LED control frequency tuning 19000Hz	248	- 255	97%	- 100%				
Projector: Risalto Led				Table name: DMX 512 function			Software version: 1.01 or following	
Table number: 352			Edition: 1	Date: 01.04.2018				