



RegoBox 5CH DMX512 350 mA

Product code: AC10005E010

KEY FEATURES

- PWM frequency adjustment from 500 to 30.000 Hz
- Max output current: 5 x 350 mA
- Max output power: 4.2 W at 12 V or 16.8 W at 48 V for each channel



SPECIFICATIONS

- Digital control at 350 mA constant current
- Directly controlled with DMX signal
- PWM frequency adjustment: from 500 to 30.000 Hz
- 31 internal programs
- 5 different electrical channels, individually controlled
- Electronic dimmer (9 selectable curves)
- Electronic strobe
- IP rating: 20

PHYSICAL SIZE

- Length: 164 mm (6.45 in)
- Width: 73 mm (2.87 in)
- Height: 38 mm (1.49 in - Weight: 0.5 Kg (1.1 lbs)
- Height: 38 mm (1.49 in)

CONTROL PROTOCOL AND PROGRAMMING

- USITT DMX512A
- DMX channels: 7 / 5
- Setting and addressing by display
- RDM (Remote Device Management)

ELECTRICAL SPECIFICATIONS AND CONNECTIONS

- DC Power: 12 V 48 V
- Max output current: 5 x 350 mA
- Max output power: 5 x (4.2 16.8) W
- DMX In/Out ports: RJ45, 5 pin locking XLR

DRAWING SIZE

