

💂 RegoBox 5CH DMX512 700 mA

Product code: AC10005E012

KEY FEATURES

- PWM frequency adjustment from 500 to 30.000 Hz
- Max output current: 5 x 700 mA
- Max output power: 8.4 W at 12 V or 33.6 W at 48 V for each channel



SPECIFICATIONS

- Digital control at 700 mA constant current
- Directly controlled with DMX signal
- PWM frequency adjustment: from 500 to 30.000 Hz
- Electronic dimmer (from 0.1 to 9.9)
- Electronic strobe
- IP rating: 20

PHYSICAL SIZE

- Length: 164 mm (6.45 in)
- Width: 73 mm (2.87 in)
- Height: 38 mm (1.49 in)
- Weight: 0.5 Kg (1.1 lbs)

CONTROL PROTOCOL AND PROGRAMMING

- USITT DMX512A - DMX channels: 5 / 1
- Setting and addressing by display
- RDM (Remote Device Management)

ELECTRICAL SPECIFICATIONS AND CONNECTIONS - DC Power: 12 V - 48 V

- Max output current: 5 x 700 mA
- Max output power: 5 x (8.4 33.6) W
- DMX In/Out ports: RJ45, 5 pin locking XLR

1

DRAWING SIZE

