

DMX Chart REGOLED (eng)

channel	function	type of control	effect	decimal	percentage
1	master dimmer	proportional	adjust luminous output intensity from 0 to 100%	0 - 255	0% - 100%
2	red	proportional	proportional control of the percentage of red colour from 0 to 100%	0 - 255	0% - 100%
2	speed	proportional	fade speed between colours from fast to slow (from 1 second to 1 minute)	0 - 255	0% - 100%
<b>Note 1:</b> channel 2 has various functions depending upon the selection made on channel 6					
3	green	proportional	proportional control of the percentage of green colour from 0 to 100%	0 - 255	0% - 100%
3	pause	proportional	control of the the pause time between colours (steps); the pause time is adjustable proportionally from 1 second to 3.30 minutes	0 - 255	0% - 100%
<b>Note 2:</b> channel 3 has various functions depending upon the selection made on channel 6					
4	blue	proportional	proportional control of the percentage of blue colour from 0 to 100%	0 - 255	0% - 100%
5	strobe effect	step	no effect	0 - 9	0% - 4%
		proportional	variable speed strobing effect, from slow to fast	10 - 57	4% - 22%
		step	stop strobe	58 - 59	23% - 23%
		proportional	sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	60 - 108	24% - 42%
		step	stop strobe	109 - 110	43% - 43%
		proportional	sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast)	111 - 159	44% - 62%
		step	stop strobe	160 - 161	63% - 63%
		proportional	random strobe effect with variable speed from slow to fast and synchronised colours	162 - 207	64% - 81%
		step	stop strobe	208 - 209	82% - 82%
proportional	random strobe effect with variable speed from slow to fast and non-synchronised colours	210 - 255	82% - 100%		
<b>Note 3:</b> if dip switch 13 is set to on, the DMX table indicates the activation of an accessory channel (5) for strobe effects					
6	automated functions	step	no effect	0 - 9	0% - 4%
			automated program 1	10 - 50	4% - 20%
			automated program 2	51 - 91	20% - 36%
			automated program 3	92 - 132	36% - 52%
			automated program 4	133 - 173	52% - 68%
			random program repeat	174 - 214	68% - 84%
			repeat all programs in sequence	215 - 255	84% - 100%
<b>Note 4:</b> pause and speed settings are added					
<b>Projector: RegoLed controller linealed      Table name: DMX 512 functions</b>					
<b>Table number: 239</b>		<b>Edition: 0</b>		<b>Date: 16/06/2004</b>	