

Otello HD VariWhite (motorized zoom version)
 DMX chart (6 ch)

channel		function	type of control	effect	decimal		percentage	
6	4							
1	1	master dimmer	proportional	adjust luminous output intensity from 0 to 100%	0	- 255	0%	- 100%
2	-	dimmer fine	proportional	fine dimmer control 16 bit	0	- 255	0%	- 100%
3	2	white tone	step	2.800 K	0	- 6	0%	- 2%
			proportional	proportional value from 2.800 K to 3.200 K	7	- 33	3%	- 13%
			step	3.200 K	34	- 60	13%	- 24%
			proportional	proportional value from 3.200 K to 4.000K	61	- 87	24%	- 34%
			step	4.000 K	88	- 114	35%	- 45%
			proportional	proportional value from 4.000 K to 5.000 K	115	- 141	45%	- 55%
			step	5.000 K	142	- 168	56%	- 66%
			proportional	proportional value from 5.000 K to 5.600 K	169	- 195	66%	- 76%
			step	5.600 K	196	- 222	77%	- 87%
			proportional	proportional value from 5.600 K to 6.500 K	223	- 249	87%	- 98%
		step	6.500 K	250	- 255	98%	- 100%	
4	-	strobe	step	no effect	0	- 9	0%	- 4%
			proportional	variable speed strobing effect, from slow to fast	10	- 57	4%	- 22%
			step	stop strobe	58	- 59	23%	- 23%
			proportional	sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	60	- 108	24%	- 42%
			step	stop strobe	109	- 110	43%	- 43%
			proportional	sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast)	111	- 159	44%	- 62%
			step	stop strobe	160	- 161	63%	- 63%
			proportional	random strobe effect with variable speed from slow to fast	162	- 207	64%	- 81%
			step	stop strobe	208	- 209	82%	- 82%
			proportional	random strobe effect with variable speed from slow to fast (warm / cold white in alternation)	210	- 255	82%	- 100%
5	3	special functions	step	park	0	- 9	0%	- 4%
				no effect	10	- 22	4%	- 9%
				reset of all the motors (only once)	23	- 35	9%	- 14%
				no effect	36	- 48	14%	- 19%
				fan at low-noise mode	49	- 61	19%	- 24%
				fan at studio mode	62	- 74	24%	- 29%
				fan at auto-silent mode	75	- 87	29%	- 34%
			proportional	fan speed control mode	88	- 100	35%	- 39%
			step	enables the automatic display blackout	101	- 113	40%	- 44%
				disables the automatic display blackout	114	- 126	45%	- 49%
no effect	127	- 255		50%	- 100%			
6	4	zoom	proportional	proportional control of zoom from narrow to wide beam	0	- 255	0%	- 100%
Projector: Otello HD VariWhite				Chart name: DMX512 function		Software version: 0.57 or following		
Edition: 4				Date: 17.02.2020				

channel	function	type of control	effect	decimal	percentage
1	master dimmer	proportional	adjust luminous output intensity from 0 to 100%	0 - 255	0% - 100%
2	dimmer fine	proportional	fine dimmer control 16 bit	0 - 255	0% - 100%
3	white tone	step	2.800 K	0 - 6	0% - 2%
		proportional	proportional value from 2.800 K to 3.200 K	7 - 33	3% - 13%
		step	3.200 K	34 - 60	13% - 24%
		proportional	proportional value from 3.200 K to 4.000K	61 - 87	24% - 34%
		step	4.000 K	88 - 114	35% - 45%
		proportional	proportional value from 4.000 K to 5.000 K	115 - 141	45% - 55%
		step	5.000 K	142 - 168	56% - 66%
		proportional	proportional value from 5.000 K to 5.600 K	169 - 195	66% - 76%
		step	5.600 K	196 - 222	77% - 87%
		proportional	proportional value from 5.600 K to 6.500 K	223 - 249	87% - 98%
step	6.500 K	250 - 255	98% - 100%		
4	strobe effect	step	no effect	0 - 9	0% - 4%
		proportional	variable speed strobing effect, from slow to fast	10 - 57	4% - 22%
		step	stop strobe	58 - 59	23% - 23%
		proportional	sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	60 - 108	24% - 42%
		step	stop strobe	109 - 110	43% - 43%
		proportional	sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast)	111 - 159	44% - 62%
		step	stop strobe	160 - 161	63% - 63%
		proportional	random strobe effect with variable speed from slow to fast	162 - 207	64% - 81%
		step	stop strobe	208 - 209	82% - 82%
		proportional	random strobe effect with variable speed from slow to fast (warm / cold white in alternation)	210 - 255	82% - 100%
5	special functions	step	park	0 - 9	0% - 4%
			no effect	10 - 48	4% - 19%
			fan at low-noise mode	49 - 61	19% - 24%
			fan at studio mode	62 - 74	24% - 29%
			fan at auto-silent mode	75 - 87	29% - 34%
		proportional	fan speed control mode	88 - 100	35% - 39%
		step	enables the automatic display blackout	101 - 113	40% - 44%
			disables the automatic display blackout	114 - 126	45% - 49%
			no effect	127 - 255	50% - 100%
Projector: Otello HD VariWhite			Chart name: DMX512 function		Software version: 0.57 or following
Edition: 4			Date: 17.02.2020		

Otello HD VariWhite (manual / P.O. version)
DMX chart (2, 1 ch)

channel		function	type of control	effect	decimal		percentage		
2	1								
1	1	master dimmer	proportional	adjust luminous output intensity from 0 to 100%	0	-	255	0% - 100%	
2	-	white tone	step	proportional value from 2.800 K to 6.500 K	0	-	255	0% - 100%	
Projector: Otello HD VariWhite				Chart name: DMX512 function		Software version: 0.57 or following			
Edition: 4				Date: 17.01.2020					